

Additional manual

Emergency battery for PULL T24, -T24speed




Important for use with emergency battery

- The motor can be equipped with an additional optional battery (NB), which can be integrated into the operator.

IMPORTANT BEFORE CONNECTION OF BATTERY:

- Mount the operator completely.
- Make the electric wiring incl. 230V connection.
- Make sure that there is a 230V power supply before connecting the battery.
- Disconnect the 4pol. clamp block (KL).
- Grey battery cable (- Pol) → connect to control terminal 18.
- Remove protection tube (S) of yellow battery cable.
- Yellow battery cable (+ Pol) → connect to control terminal 19.
- Connect the 4pol. clamp block (KL) again.



Protection against DEEP DISCHARGE of the accumulator (battery): If the system is to be disconnected from the mains supply for a longer period of time (from one day), it is absolutely necessary to disconnect the rechargeable battery from the control.



IMPORTANT

- Make the battery connection with great care, so that there is no short-circuit (the battery is pre-loaded !)
- Make sure that there is a 230V power supply before connecting the battery
- For repair and maintenance works please remove first the clamp block/terminal (KL) and then turn off the 230V power supply !
- When reconnecting again first turn on the 230V power supply and then attach the clamp block/terminal (KL).



battery set (Art.No. S35116)



Tousek Ges.m.b.H.
Österreich
A-1230 Wien
Zetschegasse 1
Tel. +43/1/667 36 01
Fax +43/1/667 89 23
info@tousek.at

Tousek GmbH
Deutschland
D-83395 Freilassing
Traunsteiner Straße 12
Tel. +49/86 54/77 66-0
Fax +49/86 54/57 196
info@tousek.de

Tousek
Benelux NV
BE-3930 Hamont - Achel
Buitenheide 2A / 1
Tel. +32/ 11/ 91 61 60
Fax +32/ 11/ 96 87 05
info@tousek.be

Tousek Sp. z o.o.
Polen
PL 43-190 Mikołów (k/Katowic)
Gliwicka 67
Tel. +48/32/738 53 65
Fax +48/32/738 53 66
info@tousek.pl

Tousek s.r.o.
Tschechische Rep.
CZ-252 61 Jeneč u Prahy
Průmyslová 499
Tel. +420 / 777 751 730
info@tousek.cz